

S70 Digital Media DJ Work Station

- Digital DJ Workstation: USB player + 2-ch Mixer + Midi Controller
- 2 USB sockets for external USB device support
- All 94 control elements are MIDI compatible for most of DJing software
- Bundle with VirtualDJ LE DJing software
- SLIP mode to make original rhythm continue play when scratching and looping
- 4 Hot Cues/Loops with Loop Roll switch to active Loop Roll function
- Quickly make a loop via Auto Beat Loop function
- Fader Start, Key Lock functions
- 4 digital sound effect: Echo, Flanger, Filter, Skid
- High quality 100 mm long pitch fader ($\pm 6\%$, $\pm 10\%$, $\pm 16\%$ and -100%)
- VOXOA TUNEBOX software makes reading and searching files quicker and easier.
- 2-ch Mixer with Three-band EQ & kill features for each band
- 2 MIC with level control, tone adjust and talkover
- Replaceable Crossfader with 3 curve switch
- Booth out with level adjust



Specification

Power: AC100-240V, 50/60Hz, 14 W
 Weight: 3.5 kg
 Size: 420 (W) x 300 (D) x 90~75(H)mm
 Frequency Response: LINE: 20~20k Hz ; PHONO: 20~20kHz ;
 MIC: 20 - 20K Hz
 S/N Ratio: LINE,: >73dB ; PHONO: > 73dB ; MIC: > 63dB
 THD + N: LINE/AUX: <0.06% ; PHONO: <0.07% ; MIC: <0.07%
 Input: Line x 4 (RCA), Aux/Phono x 4 (RCA), Microphone x 2 (XLR/1/4 Inch x 1,6.3mm x1), USB x 2
 Output: Balanced Output (XLR) x1, Unbalanced Output(RCA) x1, Booth (RCA) x1, USB MIDI x 1



Features

1. All-in-one Design

The S70 is a dual USB player and a high performance mixer in an elegant all-in-one design. Set up of the S70 is easy and fast. You just need to bring the S70 and USB storage device. It's perfect for DJs who work events, for clubs that need to be able to dismantle their system quickly. Moreover, the S70 is also a MIDI controller that can fully control any DJ software. The comprehensive MIDI compatibility all 94 control elements can be applied as a MIDI control device.



2. Memo Points with 4 Trigger Pads & Loop Roll Function

4 memo points can be saved per track for Hot Cues and Loops. The number of memo points is limited only by your USB memory capacity. This memo function can be used like a mini sampler adding a touch of creativity to any DJ set. You can just active the "Loop Roll" the 4 Pads can be switched to Loop Roll function.



3. VOXOA TUNEBOX database builder software

VOXOA TUNEBOX software makes reading and searching files much quicker and easier. The VOXOA TUNEBOX scans all of music files in your USB mass storage devices and then creates a database file by which you can quickly locate files in your music library.



4. SLIP Mode

When the SLIP mode is turned on, normal playback continues in the background with the original rhythm during scratch play, auto loop play and loop roll play. It is amazing function when you already done beat matching you can add scratch and loop roll effect.



5. Full Function 2-Channel Mixer

The S70 2-Channel Mixer has 3 band EQ for each channel with EQ KILL buttons. You can switch inputs from USB player, external player or turntable, or audio from computer via internal sound card. Moreover, you can control the deck play/stop by crossfader through the fader start function. The crossfader has two curves and through function for diversity DJing style.



6. DSP Digital Sound Effects

The S70 supplies the DJ with 4 different types of on-board DSP digital effects, including Echo, Flanger, Filter and Pan, to enhance creativity and performance. Also, effect parameters can be adjusted independently via the jog wheel.



Other Functions

- Automatic and manual tap beat counter
- Cue Play function can back to cue and play instantly
- Single and Continuous play modes
- Auto cue function cues track to start of music
- Auto Beat Loop
- Seamless loop/reloop function
- High quality 100 mm long pitch fader
- Two Touch sensitive multifunctional jog wheel for search, pitch bend and effects adjustment
- 3 modes for jog wheel: Normal CDJ, Scratch, Cue Scratch
- 2 Large extra bright dot-matrix VFD display
- Three-band EQ with Full output kill for each channel
- Fader start
- 2 MIC with level control, tone adjust and talkover
- Replaceable Crossfader with 3 curve switch
- Headphone with level control and cue mixing
- Booth out with level
- BPM sync
- Loop Roll with 1/2, 1/4, 1/8, and 1/16 beats buttons

*All specifications and appearances are subject to change without notice. VOXOA reserves the rights to change the design for products improvement.

VOXOA Co., LTD

Suite 1801-5,18/F, Tower 2, China Hong Kong City,
 33 Canton Road, Tsim Sha Tsui, Kowloon, Hong Kong
 http://www.voxoa-pro.com
 Email: service@voxoa-pro.com

VOXOA Distributor

SOUND SHINE INTERNATIONAL CO., LTD
 Tel:0755-27346188 / 0755-27347188
 E-mail: sales@soundshine.com.cn

